

KEY	
	Dimmable, with lamps on one dimmer up to a max of 10% of the max dimmer load (8 max tested)
x Max	Lamps are dimmable for up to x number of lamps only
	The majority of configurations show undesirable dimming behavior
	Configuration not tested
	Lamp is not designed for use with this dimmer type

Bulbs														Novallure		230V Reflector		MR16	
Brand	Type #	Type	Load	Bulbs			Novallure		230V Reflector		MR16								
				A55 6W	Glow	806lm	Candle	Lustre	GU10 7W PAR20	PAR30S PAR38	MR16 7W	MR16 10W							
Berker	2830 10	R	60~400W																
Berker	2866 10	RL	20~500W										(2) (2)						
BTICINO	L4406	RL	?				3 Max						(2) (2)						
Busch Jaeger	2200	RL	500W				2 Max						(2) (2)						
Busch Jaeger	2247U	RL	500W										(2) (2)						
Busch Jaeger	2250U	R	600W				3 Max												
Busch Jaeger	6513 U-102	RC	?																
Crabtree	CPU-2W400 (DL 22010/C)	?	400W		2 Max					2 max									
DANLERS	DQDGD MK400W + RESLOAD	RC	?																
Drespa	814	?	60~400W																
ELKO	RS16/400 GLI PH			1 max	3 max		2 max		1 max				(2) (2)						
Eltako	EUD61 NPN -UC	RLC	500W										(2) (2)						
Eltako	FUD61 NPN-230V	RLC	300W										(2) (2)						
Gira	1176	RLC	?																
Gira	030000/I01	R	60~400W	1 max	1 max		NO		1 max				(2) (2)						
Gira	030600/I00	RL	20~500W										(2) (2)						
Gira	226200/I00	RL	500W										(2) (2)						
Gira / Insta	030200 I00	R	60~600W				2 Max												
hager	EV012	RC	300W																
hager Kallysta	WK064	RC	60~320W																
Jung	225NV DE	RL	20~500W										(2) (2)						
Jung	266 GDE	R	60~600W				3 Max												
Legrand	67085	RLC	300W																
Legrand	67086	RLC	1000W																
LK	506DA120		350W										(2) (2)						
LK	506DA109		300W										(2) (2)						
Merten (Schneider Electric)	5771	RC	?																
MK	52471SL	?	?		3 Max														
N&L	28956/433/4	R	60~400W																
N&L	28969/435 HAN	RL	60~600W				3 Max						(2) (2)						
niko	09-013	R	60~300W				3 Max												
OPUS	852.390	R	60~400W				3 Max												
OPUS	852.392	RL	20~500W				2 Max						(2) (2)						
PEHA	435HAN	RL	60~600W										(2) (2)						
PEHA	436	R	60~600W																
RELCO	RL1724	RL	?				4 Max						(2) (2)						
Relco	RT65R0A	R	60~500W																
RELCO	RM34DSL	RL	?		2 Max								(2) (2)						
Richmond	ECU400	RL	?										(2) (2)						
RVE	RV5	RL	1000W										(2) (2)						
Schneider	400 UNI IHC/SA		40~400W	(1)	(1)	(1)	(1)		(1)				(2) (2)						
Schneider Electric	ALB45192	RL	40~400W										(2) (2)						
Schneider Electric	ALB82100	RL	40~300W																
Schneider Electric	MTN572599	RL	20~500W										(2) (2)						
Schneider Electric	MTN572299	R	60~600W																
Siemens	5TC8284	RC	20~600W																
Varilight	IOI401M	?	?																
Varilight	IQT401M	RC	400W																
Varilight	J401	?	400/250W																
VEILENDING	MDC-10-MH		10~420W		1 max		2 max						(2) (2)						

(1) This dimmer has complex installation but works well under certain configurations

(2) Testing of MR16 with Magnetic transformers (with RL type dimmers) ongoing, expect result Feb 2011